



BK3431 Bluetooth Low Energy Single Mode SoC

Preliminary Specification

Beken Corporation
3A,1278 Keyuan Rd,Zhangjiang High-Tech Park
Pudong new Distrinct,Shanghai,201203,china
Tel: (86)21 51086811
Fax: (86)21 60871277

This document contains information that may be proprietary to, and/or secrets of, Beken Corporation. The contents of this document should not be disclosed outside the companies without specific written permission.

Disclaimer: Descriptions of specific implementations are for illustrative purpose only, actual hardware implementation may differ.



Revision History

Version	Date	Author(s)	Description
0.1	18/Apr/2012	Weifeng	Initial Draft
	13/July/2012	Weifeng	Update pin list, block diagram and elec. Spec according to initial spec
1.0	2013-08-23	Zhou Guofei	Update Pin mapping and description. Update functional description of digital peripheral units.
	2013-08-26	Weifeng	Add package and order information; Correct syntax error
1.1	2013-11-27	Zhou Guofei	Add 32Pin QFG Package Update the GPIO Pin Configurations



Table of Contents

1	General Description	6
1.1	Overview	6
1.2	Block Diagram	6
1.3	Features	7
2	PIN information	8
3	Functional Description.....	10
3.1	GPIO	10
3.2	PWM and Watch Dog Timer	12
3.3	ADC	12
3.4	UART.....	13
4	Electrical Specifications.....	14
5	Application Schematic	15
6	Package Information	17
7	Ordering Information	18



List of Figures

FIGURE 1 BK3431 BLOCK DIAGRAM	6
FIGURE 2 BK3431 QFN32 PIN ASSIGNMENT.....	8



List of Tables

TABLE 1 BK3431 QFN56 PIN DESCRIPTION.....	9
TABLE 2 BK3431 GPIO FUNCTION MAPPING.....	10
TABLE 3 BK3431 GPIO WAKE-UP CONFIGURATION (BASE ADDRESS: 0X00806500)	11
TABLE 4 BK3431 RF CHARACTERISTICS.....	14

1 General Description

1.1 Overview

The BK3431 chip is a highly integrated Bluetooth 4.0 low energy single mode device. It integrates a high-performance RF transceiver, baseband, ARM-core Micro processor, rich feature peripheral units, programmable protocol and profile to support BLE application. The Flash program memory makes it suitable for customized applications.

1.2 Block Diagram




Figure 1 BK3431 Block Diagram

1.3 Features

- Bluetooth® SIG Bluetooth Low Energy Single-Mode (BLE) compliant
- Low-power 2.4GHz Transceiver
- ARM968 Core Micro processor integrated
- 128KB programmable Flash for Program and 16KB RAM for Data
- Operation voltage from 1.8 V to 3.6 V
- -89 dBm sensitivity at 1 Mbps data rate and +4dBm transmit power
- Current consumption
 - Rx Mode RF current consumption: 13mA at sensitivity level
 - Tx Mode RF current consumption: 10mA at 0dBm output power
 - IDLE Mode for established BLE connection: 20uA
 - Deep-Sleep Mode with GPIO wake-up: 2uA
- Clock
 - 16 MHz crystal reference clock
 - 24MHz optional clock provided by internal DPLL
 - Internal 32KHz low-power oscillator with auto-calibration (± 200 ppm)
 - External 32KHz crystal oscillator as optional low-power clock source
- Interface and peripheral units
 - FLASH programming, JTAG, I2C, SPI and UART interface
 - On-chip high accurate temperature sensor
 - On-chip 7-channel 10bit general ADC
- Package Type
 - 32-pin QFN 4mmx4mm package
 - 16 GPIO pins are available for various function usages such as HID, Remote Control and Wireless Beacon.

2 PIN information

The following figure shows QFN32 format packet type including 16 GPIO pins. The pin description is given in Table 1.




Figure 2 BK3431 QFN32 pin assignment

Table 1 BK3431 QFN56 Pin Description

PIN	Name	Pin Function	Description
1	P0.3	Digital I/O	General I/O for JTAG_Mode=0 JTAG Reset for JTAG_Mode=1 or data I/O for SMBUS (I2C)
2	P0.2	Digital I/O	General I/O, or clock for I2C
3	P0.1	Digital I/O	General I/O, or input for UART
4	P0.0	Digital I/O	General I/O, or output for UART
5	RSTN	Digital In	Reset for chip, active low
6	VCCRF	Power supply	3v supply
7	ANT	Antenna port	Connection of antenna to Tx and Rx
8	NC	NC	NC
9	VCCIF	Power supply	3V power supply of receiver IF path
10	ADCVREF	Analog pin	ADC reference voltage decoupling pin
11	VCCXTAL	Power output	3V power supply for crystal oscillator
12	XTALO	Analog output	Oscillator output
13	XTALI	Analog In	Oscillator input
14	P3.3	Digital I/O or analog In	General I/O, or input of General ADC ch3
15	P3.2	Digital I/O or analog In	General I/O, or input of General ADC ch2
16	XTAL32K	Analog In	32 KHz crystal input
17	VDDSPI	Analog pin	1.5V low power digital LDO output
18	VDDDSP	Analog pin	1.5V digital LDO output
19	P3.1	Digital I/O or analog In	General I/O, or input of General ADC ch1
20	P1.1	Digital I/O	General I/O, or enable for PWM1
21	P1.2	Digital I/O	General I/O, or enable for PWM2
22	P1.3	Digital I/O	General I/O, or enable for PWM3
23	P1.4	Digital I/O	General I/O, or enable for PWM4
24	JTAG_Mode	Digital In	JTAG Mode selection: 0: Disable, 1: Enable
25	VSSMCU	Power supply	Power ground for digital
26	VCCMCU	Power supply	Power supply for digital
27	Prog_Mode	Digital In	Flash Program Mode selection 0: Flash in normal mode 1: Flash in program mode
28	P1.0	Digital I/O	General I/O, or enable for PWM0
29	P0.7	Digital I/O	General IO for Prog_Mode/JTAG_Mode=0 SPI Enable for Prog_Mode=1 JTAG TMS for JTAG_Mode=1
30	P0.6	Digital I/O	General IO for Prog_Mode/JTAG_Mode=0 SPI Clock for Prog_Mode=1 JTAG Clock for JTAG_Mode=1
31	P0.5	Digital I/O	General IO for Prog_Mode/JTAG_Mode=0 SPI MISO for Prog_Mode=1 JTAG TDO for JTAG_Mode=1
32	P0.4	Digital I/O	General IO for Prog_Mode/JTAG_Mode=0 SPI MOSI for Prog_Mode=1 JTAG TDI for JTAG_Mode=1

3 Functional Description

3.1 GPIO

The BK3431 has totally 16 available GPIO pins for QFN32 package type, which can be configured as either input or output. There are secondary functions available for GPIO pins and configurable by firmware.

Table 2 BK3431 GPIO function mapping

GPIO	Program Mode	JTAG Mode	Secondary Function
GPIO P0.0			UART TXD
GPIO P0.1			UART RXD
GPIO P0.2			I2C Clock
GPIO P0.3		JTAG Reset	I2C Data IO
GPIO P0.4	SPI MOSI	JTAG TDI	SPI Interface Clock
GPIO P0.5	SPI MISO	JTAG TDO	SPI Interface MOSI
GPIO P0.6	SPI Clock	JTAG Clock	SPI Interface MISO
GPIO P0.7	SPI Enable	JTAG TMS	SPI Interface Enable
GPIO P1.0			PWM0
GPIO P1.1			PWM1
GPIO P1.2			PWM2
GPIO P1.3			PWM3
GPIO P1.4			PWM4
GPIO P3.1			ADC Channel 1
GPIO P3.2			ADC Channel 2
GPIO P3.3			ADC Channel 3

Each GPIO pin can be the source to wake up MCU from shut down state. In the shutdown state, any voltage level change on the pre-configured GPIO pin will trigger the wake-up procedure.

Each GPIO has its own configuration bits as following.

Table 3 BK3431 GPIO wake-up configuration (Base address: 0x00806500)

Address Offset	Configuration	Description
0x10	GPIO_WU_TYPE	GPIO Wake-up Mode: 1: Wake-up at positive edge 0: Wake-up at negative edge Bit[7:0] for GPIO P0.0~P0.7 Bit[15:8] for GPIO P1.0~P1.7 Bit[23:16] for GPIO P2.0~P2.7 Bit[31:24] for GPIO P3.0~P3.7
0x11	GPIO_WU_TYPE	GPIO Wake-up Mode: 1: Wake-up at positive edge 0: Wake-up at negative edge Bit[7:0] for GPIO P4.0~P4.7
0x12	GPIO_WU_ENABLE	GPIO Wake-up function enable: 1: Enable 0: Disable Bit[7:0] for GPIO P0.0~P0.7 Bit[15:8] for GPIO P1.0~P1.7 Bit[23:16] for GPIO P2.0~P2.7 Bit[31:24] for GPIO P3.0~P3.7
0x13	GPIO_WU_ENABLE	GPIO Wake-up function enable: 1: Enable 0: Disable Bit[7:0] for GPIO P4.0~P4.7
0x14	GPIO_WU_STAT	GPIO Wake-up Status. Write 1 to clear after wake-up. 1: Status active 0: None Bit[7:0] for GPIO P0.0~P0.7 Bit[15:8] for GPIO P1.0~P1.7 Bit[23:16] for GPIO P2.0~P2.7 Bit[31:24] for GPIO P3.0~P3.7
0x15	GPIO_WU_STAT	GPIO Wake-up Status. Write 1 to clear after wake-up. 1: Status active 0: None Bit[7:0] for GPIO P4.0~P4.7

3.2 PWM and Watch Dog Timer

There are five PWM timers. The clock of PWM timers can be selected as 32KHz or 16MHz by ICU register.

There are two modes of PWM timers. One is timer mode and another is PWM mode. The timer mode can generate interrupt to MCU. The PWM mode can generate PWM waveform and output to GPIO pins to drive external device such as LED. Five GPIO pins can be used to output PWM waveform separately.

The watch dog timer runs with 32 kHz clock, with period from 0.6 ms to 38 second.

3.3 ADC

A 10-bit generic ADC is integrated in BK3431. Total 8 channels can be selected for ADC transfer. All other 7 channels can be configured for different purposes except the channel 0 which is used for digitize the output of on-chip temperature sensor. The ADC supports continue mode and single transfer mode, and the sample rate can be 1 kHz to 32 kHz. In single transfer mode, it will generate interrupt every time after transform.

The ADC have four work mode, they are sleep mode, single mode, software mode and continue mode.

- Sleep mode (mode==00): ADC is power down now
- Single mode (mode==01): The system will enter sleep mode when transfer is done and waiting MCU to read the result. You should write mode=1 again for another transfer.
- Controlled by software (mode==10): In this mode, interrupt will be triggered after transfer and wait MCU to read. The interrupt will be cleared after MCU read, and then the transfer will start again.
- Continue mode (mode==11): The ADC will work at the sample rate set by register. The sample rate can be calculated by the next formula:
 - $F_{\text{sample}} = \text{input ADC clock} / (2^{(\text{ADC_CLK_RATE}+2)} / 36(\text{or } 18))$
 - The highest sample rate is 32k

The local interrupt flag of ADC need not be cleared by software; it will be set after transform and be cleared after the result has been read out. But the ADC INT stored ICU should be cleared after the ADC INT service finished.

The range of input voltage is from 0v to 1.5V. If the input voltage more than 1.5V, a resistor can be added to decrease the input voltage like the next diagram.

3.4 UART

The UART interface has 128 bytes FIFO for both TX and RX. It will generate interrupt request when there is risk or event of FIFO underflow or overflow. For the RX, it will generate interrupt if found parity bit check error or stop bit check error.

The wake-up function of UART Rx line is not available of current BK3431 project.


4 Electrical Specifications

Table 4 BK3431 RF Characteristics

Name	Parameter (Condition)	Min	Typical	Max	Unit	Comment
Operating Condition						
VCC	Voltage	1.8	3.0	3.6	V	
TEMP	Temperature	-20	+27	+85	°C	
Digital input Pin						
VIH	High level	VCC-0.3		VCC+0.3	V	
VIL	Low level	VSS		VSS+0.3	V	
Digital output Pin						
VOH	High level (IOH=-0.25mA)	VCC- 0.3		VCC	V	
VOL	Low level(IOL=0.25mA)	VSS		VSS+0.3	V	
Normal condition						
IVDD	Power Off		0.3	0.5	uA	
IVDD	Sleep current (RF OFF, 32 kHz clock)			2	uA	
IVDD	Active RX (1.8 V, 3 V)	10	13	13.5	mA	
IVDD	Active TX @ 0 dBm (1.8 V, 3 V)	9	10	11	mA	
Normal RF condition						
FOP	Operating frequency	2400		2480	MHz	
FXTAL	Crystal frequency		16		MHz	
RFSK	Air data rate		1		Mbps	
Transmitter						
PRF	Output power	-20	0	+4	dBm	
PBW	Modulation 20 dB bandwidth			1	MHz	
PRF1	Out of band emission 2 MHz		-20		dBm	
PRF2	Out of band emission 3 MHz		-30		dBm	
Dev	Transmit FM deviation	185	250	300	kHz	
Drift	Transmit drift in any position			400	Hz/us	20 kHz/ 50 us
Receiver						
Max Input	1 E-3 BER			-10	dBm	
RXSSENS	1 E-3 BER sensitivity	-91	-89	-86	dBm	
Intermodulation	Pin=-64 dBm; Punwant=-50 dBm; f0=2f1-f2, f2-f1=3 MHz or 4 MHz or 5 MHz	-25	-20	-18	dBm	
C/ICO	Co-channel C/I	8	9	10	dB	
C/I1ST	ACS C/I 1MHz	1	2	4	dB	
C/I2ND	ACS C/I 2MHz	-30	-29	-26	dB	
C/I3RD	ACS C/I 3MHz	-44	-42	-40	dB	
C/I1STI	ACS C/I Image channel	-14	-12	-11	dB	
C/I2NDI	ACS C/I 1 MHz adjacent to image channel	-26	-25	-22	dB	
Block	Block @ 2399, and 2484	-16	-14	-13	dBm	
Block	Block @ 2 GHz and 3 GHz	-16	-14	-13	dBm	


[illegible]

6 Application PCB Layout




7 Package Information

The BK3431 32-Pin uses the 4mmx4mm QFN package.



COMMON DIMENSIONS
(UNITS OF MEASURE=MILLIMETER)

SYMBOL	MIN	NOM	MAX
A	0.80	0.85	0.90
A1	0	0.02	0.05
A2	0.60	0.65	0.70
A3	0.20REF		
b	0.15	0.20	0.25
D	3.90	4.00	4.10
E	3.90	4.00	4.10
D2	2.80	2.90	3.00
E2	2.80	2.90	3.00
e	0.30	0.40	0.50
H	0.30REF		
K	0.25REF		
L	0.25	0.30	0.35
R	0.09	—	—
c1	—	0.10	—
c2	—	0.10	—





8 Ordering Information

Part number	Package	Packing	MOQ (ea)
BK3431Q32	QFN 4mmx4mm 32-Pin	Tape Reel	10 k

Remark:

MOQ: Minimum Order Quantity

射频和天线设计培训课程推荐

易迪拓培训(www.edatop.com)由数名来自于研发第一线的资深工程师发起成立,致力并专注于微波、射频、天线设计研发人才的培养;我们于 2006 年整合合并微波 EDA 网(www.mweda.com),现已发展成为国内最大的微波射频和天线设计人才培养基地,成功推出多套微波射频以及天线设计经典培训课程和 ADS、HFSS 等专业软件使用培训课程,广受客户好评;并先后与人民邮电出版社、电子工业出版社合作出版了多本专业图书,帮助数万名工程师提升了专业技术能力。客户遍布中兴通讯、研通高频、埃威航电、国人通信等多家国内知名公司,以及台湾工业技术研究院、永业科技、全一电子等多家台湾地区企业。

易迪拓培训推荐课程列表: <http://www.edatop.com/peixun/tuijian/>



射频工程师养成培训课程套装

该套装精选了射频专业基础培训课程、射频仿真设计培训课程和射频电路测量培训课程三个类别共 30 门视频培训课程和 3 本图书教材;旨在引领学员全面学习一个射频工程师需要熟悉、理解和掌握的专业知识和研发设计能力。通过套装的学习,能够让学员完全达到和胜任一个合格的射频工程师的要求...

课程网址: <http://www.edatop.com/peixun/rfe/110.html>

手机天线设计培训视频课程

该套课程全面讲授了当前手机天线相关设计技术,内容涵盖了早期的外置螺旋手机天线设计,最常用的几种手机内置天线类型——如 monopole 天线、PIFA 天线、Loop 天线和 FICA 天线的设计,以及当前高端智能手机中较常用的金属边框和全金属外壳手机天线的设计;通过该套课程的学习,可以帮助您快速、全面、系统地学习、了解和掌握各种类型的手机天线设计,以及天线及其匹配电路的设计和调试...

课程网址: <http://www.edatop.com/peixun/antenna/133.html>



WiFi 和蓝牙天线设计培训课程



该套课程是李明洋老师应邀给惠普 (HP)公司工程师讲授的 3 天员工内训课程录像,课程内容是李明洋老师十多年工作经验积累和总结,主要讲解了 WiFi 天线设计、HFSS 天线设计软件的使用,匹配电路设计调试、矢量网络分析仪的使用操作、WiFi 射频电路和 PCB Layout 知识,以及 EMC 问题的分析解决思路等内容。对于正在从事射频设计和天线设计领域工作的您,绝对值得拥有和学习!...

课程网址: <http://www.edatop.com/peixun/antenna/134.html>

CST 学习培训课程套装

该培训套装由易迪拓培训联合微波 EDA 网共同推出,是最全面、系统、专业的 CST 微波工作室培训课程套装,所有课程都由经验丰富的专家授课,视频教学,可以帮助您从零开始,全面系统地学习 CST 微波工作的各项功能及其在微波射频、天线设计等领域的设计应用。且购买该套装,还可超值赠送 3 个月免费学习答疑...

课程网址: <http://www.edatop.com/peixun/cst/24.html>



HFSS 学习培训课程套装

该套课程套装包含了本站全部 HFSS 培训课程,是迄今国内最全面、最专业的 HFSS 培训教程套装,可以帮助您从零开始,全面深入学习 HFSS 的各项功能和在多个方面的工程应用。购买套装,更可超值赠送 3 个月免费学习答疑,随时解答您学习过程中遇到的棘手问题,让您的 HFSS 学习更加轻松顺畅...

课程网址: <http://www.edatop.com/peixun/hfss/11.html>

ADS 学习培训课程套装

该套装是迄今国内最全面、最权威的 ADS 培训教程,共包含 10 门 ADS 学习培训课程。课程是由具有多年 ADS 使用经验的微波射频与通信系统设计领域资深专家讲解,并多结合设计实例,由浅入深、详细而又全面地讲解了 ADS 在微波射频电路设计、通信系统设计和电磁仿真设计方面的内容。能让您在最短的时间内学会使用 ADS,迅速提升个人技术能力,把 ADS 真正应用到实际研发工作中去,成为 ADS 设计专家...

课程网址: <http://www.edatop.com/peixun/ads/13.html>



我们的课程优势:

- ※ 成立于 2004 年,10 多年丰富的行业经验,
- ※ 一直致力并专注于微波射频和天线设计工程师的培养,更了解该行业对人才的要求
- ※ 经验丰富的一线资深工程师讲授,结合实际工程案例,直观、实用、易学

联系我们:

- ※ 易迪拓培训官网: <http://www.edatop.com>
- ※ 微波 EDA 网: <http://www.mweda.com>
- ※ 官方淘宝店: <http://shop36920890.taobao.com>